

## Etendue and Optical Throughput Calculations

*Authors: H. Zhu and P. Blackborow*

### Introduction

This note is intended to help decide whether a Laser-Driven Light Source (LDLS™) is the appropriate source for an application. In this note we will consider only the optical performance and not other benefits of the LDLS, such as stability or ultra-long life. One of the main factors to consider is whether or not the étendue of the LDLS matches the étendue of the optical system. To have an optimized throughput in an optical system, the étendue of the light source, the collecting optics, and the étendue of the light receiving optics, optical fibers or monochromators, need to be closely matched. (In this Application Note, a monochromator can also mean a spectrometer or a spectrograph.)

In addition to the term “étendue,” other terms often used are “f-number” (F/#) and “numerical aperture” (NA). Etendue and its relationship to F/# and NA of an optical system will be discussed, in addition to discussions on how to use étendue and throughput calculations to select appropriate LDLS applications. For simplicity, diffraction and coherence effects are excluded in these discussions.

### What is Etendue and Why Etendue Matching is Important for Effective Light Coupling

The term étendue comes from the French word for extent or spread. Other terms used for this property are Geometrical Extent (G), Optical Extent, and Optical Invariant. We will use G to represent étendue. For a LDLS source with relatively small cone of radiation (so paraxial optical approximation is valid), the étendue (G) of a light source is equal to the source emitting area (S) times the solid angle ( $\Omega$ ) from which the light is collected for a specific application,  $G \approx S\Omega$  [mm<sup>2</sup>-sr].

Etendue (G) describes the ability of a source to emit light or the ability of an optical system to accept light. For a monochromator, its étendue of accepting light is a function of the entrance slit area (S) times the solid angle ( $\Omega$ ) from which light is accepted. The étendue is a limiting factor for the throughput of the monochromator. A monochromator with smaller S and  $\Omega$  will have smaller étendue.

A typical optical system includes a light source, light collecting and focusing optics, a monochromator, light delivery optics and a detector. Within every optical system there is one component that has the lowest étendue (G<sub>lim</sub>) which sets the limit of the entire system, and has the biggest impact to the performance of the entire optical system. Frequently, G<sub>lim</sub> is determined by the input slit dimensions and F/# of a monochromator, or the small diameter and numerical aperture (NA) of an optical fiber. Light coming from a larger étendue component will be partially accepted by the limiting component with the lowest étendue.

Energetiq Technology, Inc.  
7 Constitution Way  
Woburn, MA 01801

Phone: +1 781 939 0763  
Fax: +1 781 939 0769

[info@energetiq.com](mailto:info@energetiq.com)  
[www.energetiq.com](http://www.energetiq.com)



## Sample Calculations of Etendue of Sources

In Table 1, étendue is calculated for the EQ-99 and EQ-1500 sources. Etendue of the source depends on the NA (or F/#) of the collection. Sample data are calculated for F/# from 1 to 12. For the étendue of the LDLS EQ-99, the emitting area used in calculations is a 100µm diameter disk, which represents a FWHM (full-width-half-maximum) diameter of a typical Xe plasma in an EQ-99 system. For the étendue of the LDLS EQ-1500, a 150µm diameter emitting area is used in the calculation.

Table 1. Typical values of F/#, NA, half-angle  $\theta_{1/2}$ , solid angle  $\Omega$  and LDLS source Etendue

F-Number F/#	Numerical Aperture NA	Half-Angle $\theta_{1/2}$ , degrees	Solid- Angle $\Omega$ , steradians	EQ-99 etendue, mm <sup>2</sup> .sr	EQ-1500 etendue, mm <sup>2</sup> .sr
1	0.447	26.6	0.663	5.2E-03	1.2E-02
2	0.243	14.0	0.188	1.5E-03	3.3E-03
3	0.164	9.5	0.085	6.7E-04	1.5E-03
4	0.124	7.1	0.049	3.8E-04	8.6E-04
5	0.100	5.7	0.031	2.4E-04	5.5E-04
6	0.083	4.8	0.022	1.7E-04	3.8E-04
7	0.071	4.1	0.016	1.3E-04	2.8E-04
8	0.062	3.6	0.012	9.6E-05	2.2E-04
9	0.055	3.2	0.010	7.6E-05	1.7E-04
10	0.050	2.9	0.008	6.2E-05	1.4E-04
11	0.045	2.6	0.006	5.1E-05	1.1E-04
12	0.042	2.4	0.005	4.3E-05	9.6E-05

For comparison purposes, deuterium (D2) lamps and a xenon (Xe) arc lamp are also calculated.

(a) D2 lamp with 500µm diameter plasma with 0.22NA collection, the étendue is 3.0E-02 [mm<sup>2</sup>-sr]

(b) D2 lamp with 1.0mm diameter plasma with 0.22NA collection, the étendue is 1.2E-01 [mm<sup>2</sup>-sr]

(Using the chart above, an EQ-99 with the same 0.22NA collection would have an étendue of ~1.4E-03 [mm<sup>2</sup>-sr])

(c) 75W Xe short arc lamp, bright emitting area (cathode spot): 0.3 x 0.5 millimeters in dimension, 0.44NA collection, the étendue is 9.1E-2 [mm<sup>2</sup>-sr].

(Using the chart above, an EQ-99 collected with the same 0.44NA would have an étendue of ~4.9E-03 [mm<sup>2</sup>-sr])

The étendues of EQ-99 and EQ-1500 are one order or more lower, at the same NA conditions, than that of D2 lamps and 75W Xe lamps.

## Sample Calculations of Etendue of Monochromator Slits and Optical Fibers

To assess the match between the source and the application, it is necessary to understand the étendue of the optics that will receive the light. The input étendue of an optical fiber is the product of the fiber NA (converted to solid angle ( $\Omega$ ) as in Table 1) and the fiber area in mm<sup>2</sup>. The input étendue of the monochromator slits is the product of the slit area in mm<sup>2</sup> and the F/# of the monochromator, (converted to solid angle ( $\Omega$ ) as in Table 1). Some typical examples are listed below. solid angle ( $\Omega'$ ) of the focused light cone equal to the acceptance solid angle of the fiber or the monochromator. There are two parameters often used to describe the light collecting properties of optical fibers, monochromators and other optical components, one is numerical aperture (NA) and the other is f-number (F/#).

(a) Core diameter 200µm optical fiber with 0.22NA, the étendue is 4.78E-03 [mm<sup>2</sup>-sr], a good match to the LDLS

(b) Core diameter 500µm optical fiber with 0.22NA, the étendue is 2.99E-02 [mm<sup>2</sup>-sr], LDLS sources can be used.

(c) Core diameter 3mm optical fiber with 0.22NA, the étendue is 1.07 [mm<sup>2</sup>-sr], étendue is large compared to LDLS, and an arc lamp may be a better solution.

(g) An F/4 monochromator with 500µm slit width and 500µm slit height, the étendue is 1.21E-02 [mm<sup>2</sup>-sr]. For applications with this level of étendue or even lower, LDLS sources have significant advantages over other conventional light sources.

(h) An F/4 monochromator with 1mm slit width and 12mm slit height, the étendue is 5.80E-01 [mm<sup>2</sup>-sr]. Under this condition a conventional arc lamp may be better matched to a monochromator than an LDLS.

## Examples of Throughput (Radiant Flux) Calculation

To understand the amount of light that will be coupled through an optical system, the radiant flux can be calculated. Radiant flux ( $\Phi$ ) is the radiation power (energy/time, W, or mW) into, for example, a fiber end or an entrance slit of a monochromator. Spectral radiant flux ( $\Phi_\lambda$ ) is the radiation power per unit wavelength [mW/nm]. They can be calculated as the product of radiance (R), or spectral radiance ( $R_\lambda$ ) with the limiting étendue ( $G_{lim}$ ):

As shown in Figure 1, the light gathering power of an optical element is characterized by Numerical Aperture (NA), and it is expressed by:

$$\Phi[\text{mW}] = R[\text{mW}/\text{mm}^2 \cdot \text{sr}] \times G_{lim}[\text{mm}^2 \cdot \text{sr}] \quad (5)$$

or

$$\Phi_\lambda[\text{mW}/\text{nm}] = R_\lambda[\text{mW}/\text{mm}^2 \cdot \text{sr} \cdot \text{nm}] \times G_{lim}[\text{mm}^2 \cdot \text{sr}] \quad (6)$$

Because the étendue, and spectral radiance must be conserved between object and image, assuming no other losses, the above terms are all we need to determine the theoretical throughput - spectral radiant flux.

When making the calculation above, the étendue value to be used is the smaller of the source étendue or the optical system étendue, i.e. the limiting étendue ( $G_{lim}$ ).

Spectral Radiance ( $R_\lambda$ ) for the EQ-99 and EQ-1500 LDLS, for 75W Xenon and for 30W D2 lamps are shown in Figure 2.




Figure 2. Spectral radiance of EQ-99 LDLS, EQ-1500 LDLS, 75W short-arc Xe lamp and D2 lamp

As an illustration, Tables 2 and 3 show the Spectral Radiant Flux into fibers of different diameters using 4 different light sources. We show the results at two wavelengths, 200nm and 300nm. The spectral radiance for the calculations is taken from Figure 2. As a result of this kind of analysis, it becomes clear which light source delivers the optimum spectral radiant flux (power/nm) for each application.

Table 2. Spectral radiant flux calculation for four sources and two fibers at 200nm Wavelength

		Spectral Radiance of Source at 200nm	Limiting Etendue	Spectral Radiant Flux	Limiting Etendue
		mW/mm <sup>2</sup> -sr-nm	mm <sup>2</sup> -sr	μW/nm	
Source	Receiving Optic				
EQ99	200 μm Fiber	8	4.77E-03	38.2	Source
EQ1500	200 μm Fiber	15	4.78E-03	71.7	Fiber
75W Xe	200 μm Fiber	1	4.78E-03	4.8	Fiber
D2	200 μm Fiber	0.1	4.78E-03	0.5	Fiber
EQ99	3 mm Fiber	8	4.77E-03	38.2	Source
EQ1500	3 mm Fiber	15	1.07E-02	161.2	Source
75W Xe	3 mm Fiber	1	9.12E-02	91.2	Source
D2	3 mm Fiber	0.1	2.99E-02	3.0	Source

Table 3. Spectral radiant flux calculation for four sources and two fibers at 300nm Wavelength

		Spectral Radiance of Source at 300nm	Limiting Etendue	Spectral Radiant Flux	Limiting Etendue
		mW/mm <sup>2</sup> -sr-nm	mm <sup>2</sup> -sr	μW/nm	
Source	Receiving Optic				
EQ99	200 μm Fiber	15	4.77E-03	71.6	Source
EQ1500	200 μm Fiber	30	4.78E-03	143.4	Fiber
75W Xe	200 μm Fiber	6	4.78E-03	28.7	Fiber
D2	200 μm Fiber	0.02	4.78E-03	0.1	Fiber
EQ99	3 mm Fiber	15	4.77E-03	71.6	Source
EQ1500	3 mm Fiber	30	1.07E-02	322.4	Source
75W Xe	3 mm Fiber	6	9.12E-02	547.4	Source
D2	3 mm Fiber	0.02	2.99E-02	0.6	Source

## Summary

- Etendue describes capabilities of a light source emitting radiation, or an optical component accepting radiation. The optical component which has the lowest étendue sets the limit Glim for the whole optical system. LDLS sources have very low étendue and are optimally used in low étendue optical systems such as small diameter fibers and monochromators with narrow slits.
- With knowledge of the limiting étendue in an optical system and the radiance or spectral radiance of the source, the radiant flux (power) or spectral radiant flux (power/nm) through the optical system can be estimated.

## About Energetiq

Energetiq Technology, Inc. is a wholly-owned subsidiary of Hamamatsu Photonics. Energetiq combines its deep understanding of the plasma physics needed for high-brightness light generation with its long experience in building rugged industrial & scientific products. The result is that users can expect the highest levels of performance combined with the highest reliability.